

1. Connect the Cord Plug to power supply. The Digital Display flashes with "H", and the Light is ON. The unit is into standby
2. 2. Press and hold LEARN button on the Opener for more than 2 seconds, the Digital Display indicates "•"
3. Press the key twice on the remote control that you wish to operate your garage door, and "•" flashes several times before it comes to "H" Now the opener has learned the code.
4. NOTE: If you want the Opener to learn additional remote codes, perform the above steps. The Opener can learn 6 remotes at most. To Erase all Remote Control Codes Press and hold LEARN button on the Opener, the Digital Display indicates "•" before it comes to "H". The codes are now erased when the Digital Display flashes with "H"